



PRODUCT INFORMATION PR-356



PR-356 is a split mounted, stand alone proximity reader with keypad for door control (no alarm bypass). It can handle 2000 cards, has 64 time-zones, year calendar, 8 access groups and can log and store events. Programming is done from the keypad or via PC and Axbase software.

It could also be used as reader or communication master in an access control system.

PROX READER for AXCESS access control

- Prox reader with keypad
- Programming from keypad or PC
- Memory for 2000 Cards/Events
- 1 relay
- 100/63 Time-Zones
- 2-card access
- 4 LED's for indication

- Time controlled Exit Button
- 8 Access Groups
- Visitor Cards
- Door Monitoring
- Year Calendar
- RS 232 for PC/Printer
- Controller with Krone LSA-slot connectors.
- Tamper switch

- Could be connected to other readers (type -22/26/36) with screened pair-twisted cable
- Dimensions:

Reader	77x182x45
Controller	120x120x30
- Power supply:
 - 12-18 V AC/DC \equiv
 - 12-30 V DC =
- Power consumption:
140 mA (max.)

AXEMA PASSAGEKONTROLL AB
Box 90215
120 23 Stockholm
Sweden

Tel: 46 8 722 40 00

<http://www.axema.se>

Fax: 46 8 722 38 00

e-mail info@axema.se